

Conventional Fire Alarm Panel



- 4 Fixed zones
- Up to 20 (32 SensoMag Series) fire detectors per zone
- Unlimited number of call points per fire zone

MAG4P is a conventional fire alarm panel certificated by EN54-2/4, providing 4 fixed zones. Up to 20 (32 SensoMAG Series) fire detectors can be connected to every fire zone. Unlimited number of call points can be connected to every of the fire zones. MAG4P is situated in a plastic box. The panel is easy for installation and maintenance and provides user-friendly daily operation. The panel is suitable for residential, small and middle office applications with protected area up to 2200m². The panel is available in different language versions for the front panel.

Features

- 4 Fixed zones
- Up to 20 (32 SensoMag Series) fire detectors per zone
- Different language versions for the front panel
- Unlimited number of call points per fire zone
- Plastic box

Technical Specifications

Main Power Supply	~230VAC ± 10%
Frequency	50/ 60Hz
Back-up Power Supply	1 battery, 12V/ 7Ah
Power Availability	0.7A
Main power supply fail consumption	50mA
Outputs (sounder circuits on the control PCB module)	2; 24V/ 0.3A fuse
Output, FAULT Relay	1; 3A@120VAC; 3A@60VDC
Output, FIRE Relay	1; 3A@120VAC; 3A@60VDC
Auxiliary output	24VDC/ 0.3A fuse
Relative humidity resistance	(93 ± 3)% @ 40°C
Weight (without battery)	2.1kg
Dimensions	749x280x110mm
Operational temperature range	0°C - +40°C

Last update: 11/2024