

# SensoIRIS MINP

## Analogue-addressable Fire Alarm Module



- Used for connection of external devices, gas detection, panic switches, etc.
- Compact size for built in mounting
- Certified according EN54-18

The SensoIRIS MINP is a compact module with one input (switch). The module monitors and transfers to control panel the state of this input - state ON or state OFF. SensoIRIS MINP is designed for built-in installation in the mounting box of the device.

### Features

- Used for connection of external devices, gas detection, panic switches, etc.
- Compact size for built in mounting
- Certified according EN54-18

### Technical Specifications

Operating Voltage Range	15- 32VDC
Permissible voltage ripple	3.0Vpp@27VDC
Max. current consumption	100µA@27Vdc
Max. cross-section of the cable	2.5mm <sup>2</sup>
Relative humidity	<93% @ +40°C
PCB Dimensions	43x25mm
Weight	12g

Last update: 04/2023